

NAME

snd_csa - Crystal Semiconductor CS461x/462x/4280 PCI bridge device driver

SYNOPSIS

To compile this driver into the kernel, place the following lines in your kernel configuration file:

```
device sound
device snd_csa
```

Alternatively, to load the driver as a module at boot time, place the following line in loader.conf(5):

```
snd_csa_load="YES"
```

DESCRIPTION

The **snd_csa** bridge driver allows the generic audio driver sound(4) to attach to Crystal Semiconductor CS461x/462x/4280 based sound cards.

HARDWARE

The **snd_csa** driver supports the following sound cards:

- ⌘ Crystal Semiconductor CS4280
- ⌘ Crystal Semiconductor CS4610
- ⌘ Crystal Semiconductor CS4611
- ⌘ Crystal Semiconductor CS4614
- ⌘ Crystal Semiconductor CS4615
- ⌘ Crystal Semiconductor CS4622
- ⌘ Crystal Semiconductor CS4624
- ⌘ Crystal Semiconductor CS4630
- ⌘ Genius Soundmaker 128 Value
- ⌘ Hercules Game Theatre XP
- ⌘ Turtle Beach Santa Cruz

Some onboard CS4610 chips are accompanied by the CS423x ISA codec instead of the CS4297 AC97 codec. Such configurations are not supported by the **snd_csa** driver yet.

SEE ALSO

sound(4)

HISTORY

The **snd_csa** device driver first appeared in FreeBSD 4.0.

AUTHORS

Seigo Tanimura <*tanimura@r.dl.itc.u-tokyo.ac.jp*>